

DVRS & VRX1000 Comparison Chart



DVRS shown with Remote Mount APX™ 7500 with 07 Control Head (Mobile Radio Sold Separately)



VRX1000 shown with Remote Mount APX™ 7500 with 07 Control Head (Mobile Radio Sold Separately)

	DVRS Trunking/Conventional Extension	VRX1000 Trunking/Conventional Extension
Size (D,W,H) <small>(Note: Does not include in-band filters)</small>	12.5" x 7" x 7"	8" x 6" x 2"
Frequency Band	VHF UHF R1 UHF R2 700 MHz 800 MHz	VHF UHF R1 & R2 Combined 700 MHz & 800 MHz Combined
Power Output	Programmable 1-10 Watts	Programmable 0.5 - 3 Watts
Weight <small>(Does not include weight of In-Band Filters)</small>	22.9 lbs - 23.6 lbs.	4.4 lbs.
Duplex Capability	YES	NO
Simplex Capability	YES	YES
Modes	Analog Digital FDMA TDMA	Analog Digital* FDMA* TDMA*
Cross Band Operation	YES	YES
In-Band Operation	YES	YES
Vehicle Mount	YES	YES
Suitcase	YES	NO
Cabinet Mount	YES	NO
Radio Compatibility	XTL™ 2500 XTL™ 5000 APX™ 6500 APX™ 7500 APX™ 8500	APX™ 4500 APX™ 6500 APX™ 7500 APX™ 8500
Price Tiering Structure	Hardware Only	Hardware & Software

* For Digital, FDMA & TDMA modes for the VRX1000, Transceiver Functional Options must be ordered